

Precision Purpose CTL-Z series

Medium size standard AC current sensor for precise measurement for both of PCB and panel mounting

AC current sensor




Model CTL-12-S30-10Z


[Features]

- Medium size standard current sensor of $\phi 12$ aperture diameter for precise measurement
- Covering the wide range of $1\text{mA} \sim 100\text{A}$ with adoption of permalloy core of high magnetic permeability
- Possible to interface to electrical circuit directly with high current ratio of 1000:1
- Robust structure with output terminal of round pins ($\phi 2.36 \times 9\text{L}$). Possible to correspond to soldering to wire, and connector set, sold separately
- Prepared mounting bracket sold separately (HLD-12) for panel mounting

[Outline drawing]



[Output voltage characteristics]




[Specification] Ta=25°C

Model	CTL-12-S30-10Z
Primary current	1mA ~ 100Arms (50 / 60Hz), $R_L \leq 10\Omega$
Maximum primary current	250Arms continuous
Saturation limited current	130Arms (50 / 60Hz), $R_L \leq 1\Omega$
Output characteristics	Refer "Output voltage characteristics"
Linearity	Refer "Coupling efficiency [K] characteristics" (Use the flat range of [K] characteristic in the application as the linear sensor)
Secondary windings (n)	1000 ± 2 turn
Secondary windings resistance	31Ω (reference)
Withstand voltage	AC2000V(50/60Hz), 1min(between aperture and output terminal in a lump)
Insulation resistance	DC500V, $\geq 100\text{M}\Omega$ (between aperture and output terminal in a lump)
Operating temperature	-20°C ~ +75°C, $\leq 80\%RH$, no condensation
Storage temperature	-30°C ~ +90°C, $\leq 80\%RH$, no condensation
Structure	PBT plastic case, potted by epoxy on one side
Output terminal	$\phi 2.36 \times 9\text{L}$ (round pins), tin plating
Screw torque	0.3N · m
Mass	approximately 52g

- Remark (1) Output voltage is changed by the penetrated current/load resistor/[K] characteristic and so on. Please set up the condition for use with careful investigation of each characteristic
- (2) Please use with enough margin in the range of coupling efficiency [K] ≤ 0.9 , because it is the range to happen the individual difference.
- (3) Opening the secondary during turn ON is hazardous and the cause of failure, because of generating high voltage
- (4) Please be careful of CT heating in case to use with high frequency, although this CT is basically used at 50/60Hz.
- (5) Please refer Appendix-1 accessories list for accessories

[Coupling efficiency (K) characteristics]



[Frequency characteristics]

